



MODEL SDC003

## LANSHARC™ SMART DIGITAL CONTROLLER

- Integral ICP® Sensor Power
- Affordable Digital Signal Processor
- 24 Bit Delta Sigma Analog to Digital Converter
- 20 Hz to 5 or 40 kHz Real-Time Bandwidth Across 4 Channels
- Integral IEEE P1451.4 TEDS Support

## PROCESS VIBRATION SIMPLIFIED

The LanSharc™ Smart Digital Controller has been developed as a highly programmable and configurable platform for advanced machine process vibration applications development and deployment. It is designed for applications that protect critical process machinery and systems from either failure or degradation. As such, it combines analog to digital conversion and digital signal processing technology with ample memory and communications resources.

The LanSharc™ package supports two different development environments: Monitor DLL API Library and LanSharc™ Developer Kit. The standard package includes a complete DLL API library that allows the user to easily interface with the LanSharc™ from any C or Visual Basic program. This interface will enable the user to generate stand-alone application software or to integrate the LanSharc™ into a complete monitoring system.

The developer kit allows advanced users to develop proprietary algorithms programmed within firmware for their own use. This kit includes sample firmware source code and a firmware programmer's guide. Combined with user supplied Analog Devices' VisualDSP++™ for Sharc® and ADDS-SUMMIT-ICE, the developer can load these custom algorithms into their LanSharc™ unit.

SPECIFICATIONS	
<b>Performance</b>	
Inputs	
Dynamic Channels	1-4, Vibration or Acoustic Channels, TEDS capable
Static Channels	0-4 Channels, 12 Bit, 0 - 5 volt
Digital	1 Tachometer, 1 Static Digital
Dynamic Inputs	
Ranges	± 2.5 V
ICP® Interface	5 ± 1 mA IEEE P 1451.4 support
AC Coupling	-3 dB @ 20 Hz (or -3 dB @ 0.5 Hz)
Maximum Frequency Range	5 kHz or 40 kHz
Channel Crosstalk	< -90 dB
Amplitude Accuracy	< 3%
Amplitude Match	< 1%
Phase Match	5°
Harmonic Distortion	-70 dB
Dynamic Range	110 dB Typical
Static Input	
Voltage Range	0 to + 5 V pk
Input Impedance	>100 kΩ
Maximum Frequency	5 Hz
Coupling	DC
Digital Input	
Voltage Range	Approx 2 V @ 10-50 mA
Polarity	Any
Drive Current	(10-50) mA
Isolation	600 V
Digital Signal Processing	
Primary ADC	24-bit Delta Sigma
Maximum Sampling Rate	128 kHz
Block Length	Application Dependent
Overall Units	Application Dependent
DSP	32-bit Floating Point DSP Processor
Memory	16 MB SDRAM and 8 MB Flash
Microcontroller	8-bit 8051 core Microcontroller
Output	
Status	LED's indicate target machine status (3 green, 1 red)
Relay	Solid State, optically isolated 100 volts @ 120 mA (4)
Analog Output	2 Channels, 4-20 mA
Mechanical	
Protection	NEMA 4

SPECIFICATIONS (continued)	
Enclosure	2 X 4 X 7 inches aluminum
Power	24 VDC, ≤ 150 mA
Environment	Non-incendive Environment with Temperature Varying from 32° to 122° F (0° to 50° C) and 95 % Non-condensing Humidity
Communication	
Host Computer	RS-232
Network	Ethernet - TCP/IP
<b>Optional Accessories</b>	
<b>SDC003-1H</b>	LanSharc Process Analysis Box, 1 dynamic input channel
<b>SDC003-2H</b>	LanSharc Process Analysis Box, 2 dynamic input channels
<b>SDC003-4H</b>	LanSharc Process Analysis Box, 4 dynamic input channels
<b>SDC003-LF1</b>	LanSharc low frequency option for 1 channel unit, -3 dB at 0.5 Hz
<b>SDC003-LF2</b>	LanSharc low frequency option for 2 channel unit, -3 dB at 0.5 Hz
<b>SDC003-LF4</b>	LanSharc low frequency option for 4 channel unit, -3 dB at 0.5 Hz
<b>SDC003-LAN2</b>	LanSharc hardware option, internal ethernet
<b>SDC003-BEAR</b>	Band Energy Alert Recorder application firmware/software for Model SDC003 LanSharc hardware platform



10310 Aerohub Boulevard, Cincinnati, OH 45215 USA

Toll-Free in the USA: 800 860 4867

Phone: 1 513 351 9919 | Email: info@modalshop.com

The Modal Shop, Inc. offers structural vibration and acoustic sensing systems and services for various applications in design and test laboratories as well as manufacturing plants. An extensive sound and vibration rental program, precision calibration systems, and both modal and vibration shakers are designed to simplify test phases. Non Destructive Testing Systems help manufacturers provide 100% quality inspection of metal components. The Modal Shop, Inc. is a subsidiary of PCB Piezotronics, Inc., and PCB® is a wholly owned subsidiary of MTS Systems Corporation.

© 2019 The Modal Shop, Inc. In the interest of constant product improvement, specifications are subject to change without notice. PCB®, ICP®, Swiveler®, Modally Tuned®, and IMI® with associated logo are registered trademarks of PCB Piezotronics, Inc. in the United States. ICP® is a registered trademark of PCB Piezotronics Europe GmbH in Germany and other countries. UHT-12™ is a trademark of PCB Piezotronics, Inc. SensorLine™ is a service mark of PCB Piezotronics, Inc. SWIFT® is a registered trademark of MTS Systems Corporation in the United States. All other trademarks are property of their respective owners.

DS-0021 revB



MTS Sensors, a division of MTS Systems Corporation (NASDAQ: MTSC), vastly expanded its range of products and solutions after MTS acquired PCB Piezotronics, Inc. in July, 2016. PCB Piezotronics, Inc. is a wholly owned subsidiary of MTS Systems Corp.; IMI Sensors and Larson Davis are divisions of PCB Piezotronics, Inc.; Accumetrics, Inc. and The Modal Shop, Inc. are subsidiaries of PCB Piezotronics, Inc.